

JAZZ – DIE EINSTEIGERKLASSE

MERKMALE

- Frei programmierbare, umfangreiche SPS-Steuerlogik
- 2-zeiliges Text-Display
- Analoge und digitale Ein-/Ausgänge
- Schnelle Zähler, Frequenzmesser
- Integrierte PID-Regelfunktion mit Autotune
- Modbus RTU und Modbus TCP Kommunikation
- Fernsteuerung & Fernüberwachung per GSM/GPRS/SMS mit optionalem Modem
- Programmiersoftware U90Ladder im Lieferumfang enthalten
- Nur eine Software für Steuerlogik und Display / Tastatur
- Umfangreiche Software Tools wie Remote Access, OPC-Server uvm.
- Montage auf DIN-Schiene oder Schalttafeleinbau



Die Jazz ist eine Mini-SPS mit frei programmierbarer Steuerlogik, Bedieneinheit, eingebauten E/A und sehr gutem Preis-/Leistungsverhältnis.

Mit bis zu 40 analogen und digitalen Ein-/Ausgängen, 2-zeiligem Display und Tastatur ist sie ideal zur Steuerung kleiner Maschinen und für einfache Automatisierungsaufgaben geeignet.

Die Geräte zeichnen sich durch eine vollständig flache Front aus. Das 2 x 16 Zeichen Display und alle 16 Tasten sind individuell programmierbar.

Die Jazz verfügt über einen Mini-USB-Port zur Programmierung und kann optional mit einer Ethernet-Schnittstelle ausgerüstet werden.

JAZZ™ PLC+HMI

Technical Specifications

JZ20-R10/JZ20-J-R10

- 6 Digital Inputs including 2 HSC, 4 Relay Outputs

JZ20-R16/JZ20-J-R16

- 6 Digital Inputs including 2 HSC, 2 Analog/Digital Inputs, 2 Analog Inputs, 6 Relay Outputs

JZ20-J-R16HS Art. No. 147885

- 6 Digital Inputs including 3 HSC/Shaft-encoder, 2 Analog/Digital Inputs, 2 Analog Inputs, 6 Relay Outputs

This guide provides specifications for Unitronics' Micro-PLC+HMI™ JZ20-R10/JZ20-J-R10, JZ20-R16/JZ20-J-R16 and JZ20-J-R16HS.

You can find additional documentation in the Technical Library at www.unitronics.com.

Technical Specifications

Power supply

Input voltage	24VDC	
Permissible range	20.4-28.8VDC with less than 10% ripple	
Current Consumption	See Note 1	
	JZ20-R10/JZ20-J-R10	JZ20-R16/JZ20-J-R16/JZ20-J-R16HS
Max. current consumption	120mA@24VDC	136mA@24VDC
Typical power consumption	2.4W	2.6W

Notes:

1. To calculate the actual power consumption, subtract the current for each unused relay output and LCD backlight (if unused) from the maximum current consumption value.

	Per relay output	LCD backlight
Max. current per element	8.3mA@24VDC	35mA@24VDC

Battery

Back-up	7 years typical at 25°C, battery back-up for RTC and system data, including variable data.
---------	--

Digital Inputs

Number of inputs	JZ20-R10/JZ20-J-R10	JZ20-R16/JZ20-J-R16/JZ20-J-R16HS
	6 (one group). See Note 2	8 (two groups). See Notes 2 & 3
Input type	pnp (source) or npn (sink)	
Galvanic isolation	None	
Nominal input voltage	24VDC	
Input voltage		
pnp (source)	0-5VDC for Logic '0' 17-28.8VDC for Logic '1'	
npn (sink)	17-28.8VDC for Logic '0' 0-5VDC for Logic '1'	
	I0-I5	I6-I7
Input current	3.7mA@24VDC	1.2mA@24VDC
Response time	10mSec typical	20mSec typical
Input cable length	Up to 100 meters, unshielded	
High speed inputs	Specifications below apply when wired as HSC/Shaft-encoder. See Notes 4 & 5.	
Resolution	16-bit	
Frequency	10kHz maximum	
Minimum pulse width	40µs	

Notes:

2. All products comprise I0-I5; these inputs are arranged in a single group. Via wiring, the entire group may be set to either pnp or npn.
3. Only JZ20-R16/JZ20-J-R16 and JZ20-J-R16HS comprises I6 & I7. These may be wired as either digital or analog inputs, as shown in the JZ20-R16/JZ20-J-R16 and JZ20-J-R16HS Micro PLC Installation guide. I6 & I7 may be wired as npn, pnp, or 0-10V analog inputs. I1 input may be wired as pnp, while the other is wired as analog. If I1 input is wired as npn, the other may **not** be wired as analog.
4. Only in JZ20-R10/JZ20-J-R10 and JZ20-R16/JZ20-J-R16:
 - I0 and I1 can each function as either a high-speed counter or as a normal digital input.
 - When used as a normal digital input, normal input specifications apply.
5. Only in JZ20-J-R16HS:
 - I0, I1, and I4 can function as high-speed counters, as part of a shaft-encoder, or as normal digital inputs.
 - I2, I3, and I5 can function as either counter reset, as part of a shaft-encoder, or as normal digital inputs.
 - If I0, I1, I4 are set as high-speed counters (without reset), I2, I3, I5 can function as normal digital inputs.
 - When used as a normal digital input, normal input specifications apply.

Digital Outputs

	JZ20-R10/JZ20-J-R10	JZ20-R16/JZ20-J-R16/JZ20-J-R16HS
Number of outputs	4 relay	6 relay
Output type	SPST-NO (Form A)	
Isolation	By relay	
Type of relay	Panasonic JQ1AP-24V or compatible	
Output current	5A maximum (resistive load)	
Rated voltage	250VAC / 24VDC	
Minimum load	1mA@5VDC	
Life expectancy	50k operations at maximum load	
Response time	10mS (typical)	
Contact protection	External precautions required (see Increasing Contact Life Span in the product's Installation Guide)	

Analog Inputs

	JZ20-R16/JZ20-J-R16 and JZ20-J-R16HS only	
Number of inputs	4, according to wiring as described above in Note 3	
	AN0 and AN1	AN2 and AN3
Input range	0-20mA, 4-20mA	0-10VDC
Input impedance	154Ω	20KΩ
Maximum input rating	30mA	28.8V
Galvanic isolation	None	
Conversion method	Successive approximation	
Resolution	10 or 12-bit (0 to 4095) (Via Software)	
Conversion time	All analog inputs are updated every 8 PLC scans, regardless of how many inputs are actually configured.	
Precision	± 2%	
Status indication	Yes – if an analog input deviates above the permissible range, its value will be 4096.	
Input cable length	Up to 30 meters, shielded twisted pair	

Display

Type	STN LCD
Illumination backlight	LED, yellow-green, software controlled (LCD backlight; enables the display to be viewed in the dark)
Display size	2 lines, 16 characters long
Character size	5x8 matrix, 2.95x5.55mm

Keyboard

Number of keys	16 keys, including 10 user-labeled keys
Key type	Metal dome, sealed membrane switch
Slides	Slides may be installed in the operating panel faceplate to custom-label the keys and logo picture. An extra logo slide is included. A complete set of blank slides is available by separate order.

Program

Ladder code memory	48k (virtual)
Execution time	1.5 µSec for bit operations (typical)
Memory bits (coils)	256
Memory integers (registers), 16 bit	256
Timers	64
HMI displays	60 user-designed displays available
HMI variables	64 HMI variables are available to conditionally display text and data. List variables add up to 1.5k's worth of HMI capacity.

Communication

GSM-support	Via a built-in USB port or - Add-On module. See Note 6-9 SMS messages to/from 6 phone GSM numbers, up to 1K of user-designed messages. Supports Remote Access.
MODBUS	Supports MODBUS protocol, Master-Slave
Baud rate	According to add-on port module
USB	
Port type	Mini-B
Galvanic isolation	No
Specification	USB 2.0 compliant; full speed
Baud rate range	300 to 115200 bps
Cable	USB 2.0 compliant; up to 3m

Notes:

6. The JZ20 built-in USB port may be used for programming. Add-on Modules are available by separate order for communication and cloning. Note that the USB port and an Add-on module cannot be physically connected at the same time
7. Add-on module JZ-PRG, with 6-wires communication cable (supplied in PRG kit – see the JZ-PRG Installation Guide) can be used:
 - for programming
 - to connect a modem
8. Add-on module JZ-RS4 (RS232/485), with a standard 4-wire communication cable can be used:
 - for programming
 - to communicate with other devices (including modems/GSM)
 - for RS485 networking.
9. Add-on module MJ20-ET1 enables communication over 100 Mbit/s TCP/IP network:
 - Programming/data exchange with Unitronics software;
 - Data exchange via MODBUS TCP as Master or Slave.

Miscellaneous

Clock (RTC)	Real-time clock functions (date and time).
-------------	--

Environmental

Operating temperature	0° to 50°C (32° to 122°F)
Storage temperature	-20° to 60° C (-4° to 140°F)
Relative humidity (RH)	10% to 95% (non-condensing)
Mounting method	Panel mounted (IP65/NEMA4X) DIN-rail mounted (IP20/NEMA1)

Dimensions

Size	147.5 x 117 x 46.6mm (5.807" x 4.606" x 1.835"). See Note 10
Weight	300 g (10.6 oz)

Notes:

10. For exact dimensions, refer to the product's Installation Guide.

Mounting

Panel mounting	Insert into cut-out: 117 x 89mm (WxH) 4.606"x 3.504"
DIN-rail mounting	Snap unit onto the DIN rail

The information in this document reflects products at the date of printing. Unitronics reserves the right, subject to all applicable laws, at any time, at its sole discretion, and without notice, to discontinue or change the features, designs, materials and other specifications of its products, and to either permanently or temporarily withdraw any of the foregoing from the market.

All information in this document is provided "as is" without warranty of any kind, either expressed or implied, including but not limited to any implied warranties of merchantability, fitness for a particular purpose, or non-infringement. Unitronics assumes no responsibility for errors or omissions in the information presented in this document. In no event shall Unitronics be liable for any special, incidental, indirect or consequential damages of any kind, or any damages whatsoever arising out of or in connection with the use or performance of this information.

The tradenames, trademarks, logos and service marks presented in this document, including their design, are the property of Unitronics (1989) (R^G) Ltd. or other third parties and you are not permitted to use them without the prior written consent of Unitronics or such third party as may own them.